

Technical Data Sheet

BASADUR[®] E 326 Self-Leveling Flooring| Solvent-free| Antistatic| 20%

Uses

It can be used as the self-leveling top layer in ESD protection areas with medium and heavy traffic loads.

Also Available from BASA Polymer

Primers

BASADUR[®] E 101 BASADUR[®] E 102 BASADUR[®] E 103 BASADUR[®] E 105 BASADUR[®] E 112

Middle Coats

BASADUR[®] E 202 BASADUR[®] E 201 BASADUR[®] E 302

Benefits

- ESD protective and antistatic flooring
- Hard-wearing and great mechanical properties
- Low viscosity and very easy application
- Viscosity rather than BASADUR® E 325

Technical Information

Properties	
Solid Content (%) (ASTM D2369)	~ 99.5
Mix Ratio by weight	100:20
Pot Life at 25°C (min)	40
Mixed Density (g/cm ³) (ISO 2811)	1.7 approx.
Dry-Hard Time (hr.)	12
Recommended Coverage (g/m ²)	1500-1700
Overcoat Time (hr.)	8 - 24
Bond Strength (MPa) (ASTM D4541)	> 1.5 (concrete failure)
Shore D Hardness (ASTM D2240)	82(after 7 days)
Electrical Surface Resistivity (Ω) (ASTM F150-06)	<107

Shelf Life

Maximum 4 months since the date of production.

Safety information

Please check the SDS of BASADUR® E 326.

Packaging

Part A: 20.8 kg containers, 200 kg drums Part B: 4.2 kg containers, 200 kg drums

🞗 Init 18, No. 21, Boostan 1st, Ayatollah Kashani Blvd., Tehran, Iran. 🛛 🔍 98 21 44960014

Description

BASADUR[®] E 326 is a pigmented solvent-free, twocomponent, antistatic, and self-level flooring. Seamless, moderate pot life and good mechanical and physical properties are some of its properties.

Substrate Requirements and Preparation

The substrate's compressional strength should be a minimum of 20 N/mm2, and the substrate should be less than 3% moist. The substrate has to be prepared by a suitable mechanical or chemical process to remove any oil, dirt, and residues of alkali compounds. Weak areas of the concrete must be removed completely. You can use BASADUR® products to repair substrate, fill cavities, holes, and cracks. Before applying the coating, remove all dust from the substrate with a vacuum cleaner. To install antistatic flooring, first, apply a selfleveling floor coating on a primed substrate. After placing a conductive network on the floor, the antistatic primer must be applied. Then the surface is ready to install the selfleveling antistatic flooring.

Storage

The product must be stored in its original packaging in a dry place at a temperature range of 15s to 25 °C.

Legal Note

The information, and, in particular, the recommendations relating to the application and enduse of BASADURS, are given in good faith based on BASADURS's current knowledge and experience of the products when properly stored, handled, and applied under normal conditions by BASA's recommendations. In practice, the differences in materials, substrates, and actual site conditions are such that no warranty in respect of merchantability or of fitness for a particular purpose, nor any liability arising out of any legal relationship whatsoever, can be inferred either from this information, or from any written recommendations, or from any other advice offered. The user of the product must test the product's suitability for the intended application and purpose. BASA Polymer reserves the right to change the properties of its products. The proprietary rights of third parties must be observed. All orders are accepted subject to our current terms of sale and delivery. Users must always refer to the most recent issue of the local Product Data Sheet for the product concerned, copies of which will be supplied on request.

info@basapolymer.com

